

Item No. 11348

Delock 2 > 1 VGA KVM Switch with USB and Audio

Description

This Delock KVM switch is a convenient solution for connecting one monitor, beamer etc. to two computer. Furthermore the two USB ports enable you to connect a mouse and keyboard and to switch between both computers just by using the button or keyboard.

In addition you can transmit audio signals in order to use a speaker and microphone with the help of the switch on both computers.



Specification

- Connector:
 - 2 x VGA 15 pin female (connection to PC 1 and PC 2)
 - 1 x VGA 15 pin female (monitor or beamer)
 - 2 x USB 2.0 Type-A female (keyboard and mouse)
 - 2 x USB 2.0 Type-B female (connection to PC 1 and PC 2)
 - 2 x 3.5 mm stereo jack (1 x speaker, 1 x microphone)
 - 4 x 3.5 mm stereo jack (speaker and microphone connection to PC 1 and PC 2)
 - 1 x PS/2 female (keyboard)
 - 1 x DC power (only when using switch on notebook)
- 1 x button with LED indicator for PC 1 or PC 2
- Switching via button or Hotkey (keyboard Scroll Lock)
- Scan interval: 8 sec.
- Resolution: max. 1920 x 1440
- Bandwidth: 250 MHz
- USB Bus Power, for the switch there is no additional power supply needed (for connection to a notebook there may not be enough power so that you need an additional power supply DC 5 V / 0.5 – 1.0 A)
- Colour: black
- Dimension of the box incl. connector (LxWxH): ca. 12 x 9 x 3 cm
- OS independent, no driver installation necessary

System requirements

- 2 computer with each 1 x VGA female + 1 x USB A female
- Additional 1 x 3.5 mm stereo jack for speaker, 1 x 3.5 mm stereo jack for microphone
- Monitor, beamer or similar device with VGA cable

Package content

- KVM switch with USB and audio
- 2 x cable set, length: ca. 1.5 m
- User manual

Additional Information

EAN: 4043619113484

Country of origin: China

Package: Retail Box



Images

