

Item No. 11349

Delock 4 > 1 VGA KVM Switch with USB and Audio

Description

This Delock KVM switch is a convenient solution for connecting one monitor, beamer etc. to four computer. Furthermore the two USB ports enable you to connect a mouse and keyboard and to switch between all computers just by using the button or keyboard.

In addition you have the possibility to transmit audio signals so that you can use a speaker and microphone with the help of the switch on both computers.



Specification

- Connector:
 - 4 x VGA 15 pin female (connection to PC 1, PC 2, PC 3 and PC 4)
 - 1 x VGA 15 pin female (monitor or beamer)
 - 2 x USB 2.0 Type-A female (keyboard and mouse)
 - 4 x USB 2.0 Type-B female (connection to PC 1, PC 2, PC 3 and PC 4)
 - 2 x 3.5 mm stereo jack (1 x speaker, 1 x microphone)
 - 8 x 3.5mm stereo jack (speaker and microphone connection to PC 1, PC 2, PC 3 and PC 4)
 - 1 x PS/2 female (keyboard)
 - 1 x DC power (only when using switch on notebook)
- 1 x button with LED indicator for PC 1, PC 2, PC 3 and PC 4
- Switching via button or Hotkey (keyboard Scroll Lock)
- Scan interval: 8 sec.
- Resolution: max. 1920 x 1440
- Bandwidth: 250 MHz
- USB Bus Power, for the switch there is no additional power supply needed (for connection to a notebook there may not be enough power so that you need an additional power supply DC 5 V / 0.5 – 1.0 A)
- Colour: black
- Dimension of the box incl. connector (LxWxH): ca. 20.5 x 9 x 3 cm
- OS independent, no driver installation necessary

System requirements

- Up to 4 computer with each 1 x VGA female + 1 x USB A female
- Additional 1 x 3.5 mm stereo jack for speaker, 1 x 3.5 mm stereo jack for microphone
- Monitor, beamer or similar device with VGA cable

Package content

- KVM switch with USB and audio
- 4 x cable set, length: ca. 1.5 m
- User manual

Additional Information

EAN: 4043619113491

Country of origin: China

Package: Retail Box



Images

