

Delock Antenna kábel I-PEX Inc., MHF® I-dugó apa I-PEX Inc., MHF® I-dugó 1,13 4,5 cm

Leírás

A Delock antennakábel alkalmas a rádiófrekvenciás technológia komponenseinek csatlakoztatására.



Tételszám 12607

EAN: 4043619126071

Származási hely: Taiwan,
Republic of China

Csomag: Zárható
műanyag tasak

Műszaki adatok

- Csatlakozó:
1 x I-PEX Inc., MHF® I-dugó >
1 x I-PEX Inc., MHF® 4L dugó
- Impedancia: 50 Ohm
- Kábel típusa: 1.13
- Kábel: koaxiális
- Kábel csillapítás: 3,2 dB @ 2,4 GHz / méter
- Kábelátmérő: kb. 1,13 mm
- Legkisebb hajlítási sugár: 4,5 mm
- Kábel színe: fekete
- Kábelhosszúság a csatlakozóval együtt: kb. 4,5 cm

Rendszerkövetelmények

- Eszköz két szabad I-PEX Inc., MHF® 4L kapcsolóval

- Antennakábel

Figure 1: Schematic representation of the experimental design. The figure shows four panels (a, b, c, d) illustrating the experimental design for the four conditions. Each panel displays a timeline from 0 to 10 seconds, with a 5-second step delay. The top part of each panel shows the stimulus (a 10-second audio clip) and the corresponding response (a 10-second audio clip). The bottom part of each panel shows the response (a 10-second audio clip) and the corresponding stimulus (a 10-second audio clip). The panels are labeled: (a) 10-second audio clip, (b) 10-second audio clip, (c) 10-second audio clip, and (d) 10-second audio clip.

Interface

Csatlakozó 1:	1 x I-PEX Inc., MHF® 4L-dugó
Csatlakozó 2:	1 x I-PEX Inc., MHF® 4L-dugó

Technical characteristics

Impedancia:	50 Ω
-------------	------

Physical characteristics

Cable category:	koaxiális
Cable type:	1.13
Cable attenuation:	3.2 dB @ 2.4 GHz per meter
Kábel színe:	fekete
Cable length incl. connector:	4,5 cm
Legkisebb hajlítási sugár:	4,5 mm