

# Delock Converter USB 3.0 > SATA 6 Gb/s / IDE 40 pin / IDE 44 pin with backup function

## Description

This converter by Delock enables the connection of 2.5" or 3.5" IDE and SATA drives to a USB port of the PC or laptop. Thus it can be connected the drive, without an external enclosure, directly to the USB port. The included power supply provides power for the converter and the connected drives. The backup function allows backups from PC or laptop to a connected hard drive or SSD.



## Specification

- Connectors:
  - 1 x USB Type Micro-B female
  - 1 x DC jack
  - 1 x 4 pin power connector
  - 1 x SATA 6 Gb/s 22 pin receptacle
  - 1 x IDE 40 pin female
  - 1 x IDE 44 pin female
- Function key:
  - 1 x On / Off switch
  - 1 x backup button
- For hard drives, SSD, optical drive
- Data transfer rate:
  - USB 3.0 up to 5 Gb/s
  - SATA up to 6 Gb/s
  - IDE up to 133 Mb/s
- With backup function
- Allows simultaneous usage with two IDE drives and a SATA drive
- LED indicator
- Plug & Play

## Power supply specification

- Wall power supply
- Input: AC 100 ~ 240 V / 50 ~ 60 Hz / 0.8 A
- Output: 12 V / 2 A
- Ground outside, plus inside
- Dimensions:
  - inside: ø ca. 2.5 mm
  - outside: ø ca. 5.5 mm
  - length: ca. 9.5 mm

## System requirements

- Windows Vista/Vista-64/7/7-64/8.1/8.1-64/10/10-64
- PC or laptop with a free USB Type-A port

## Package content

- Converter USB 3.0 > SATA / IDE
- USB 3.0 cable
- Power cable
- External power supply

## Item no. 61486

EAN: 4043619614868

Country of origin: China

Package: Retail Box



- CD ROM with software
- User manual

Images

