

# Delock USB Docking Station Dual DisplayPort 4K / USB 3.2 / LAN / Audio (Displaylink)

#### **Description**

This docking station by Delock can be connected to a computer with a USB-C<sup>TM</sup> or USB Type-A port and provides a variety of interfaces. Two monitors can be operated simultaneously at the DisplayPort output ports. Six built-in USB 3.2 Gen 1 ports allow the use of peripherals, and connections for microphone and speaker and Gigabit network complete the features.



**Ultra-HD (4K) resolution** is possible when using only one monitor and also when using both DisplayPort outputs at the same time. There is no DisplayPort Alternate Mode support required.

#### **Extended screen by Displaylink**

Due to the Displaylink graphics chipset it is possible to usemirrored and extended screen functions on Windows and Mac OS operating systems.



#### Item no. 87728

EAN: 4043619877287 Country of origin: China Package: Retail Box

### **Specification**

· Connectors:

front side:

- 1 x SuperSpeed USB 5 Gbps (USB 3.2 Gen 1) Type-A female
- 1 x SuperSpeed USB 5 Gbps (USB 3.2 Gen 1) Type-A female Battery Charging specification BC1.2
- 1 x microphone 3.5 mm stereo jack
- 1 x speaker 3.5 mm stereo jack

back side:

- 4 x SuperSpeed USB 5 Gbps (USB 3.2 Gen 1) Type-A female
- 2 x DisplayPort female
- 1 x Gigabit LAN 10/100/1000 Mbps RJ45 jack
- 1 x SuperSpeed USB 5 Gbps (USB 3.2 Gen 1) Type-B female
- 1 x DC 20 V power connector
- Maximum resolution (depending on the system and the connected hardware):
   Single display: up to 3840 x 2160 @ 60 Hz

#### **DATASHEET**



Dual display: up to 3840 x 2160 @ 60 Hz

- · Transmission of audio and video signals
- Functions: Mirrored or Extended
- 1 x On / Off switch
- · Colour: black
- Dimensions without stand (LxWxH): ca. 190 x 78 x 38 mm

## Power supply specification

- · Wall power supply
- Input: AC 100 ~ 240 V / 50 ~ 60 Hz / 1.3 A
- Output: 20 V / 2.25 A
- · Ground outside, plus inside
- Dimensions:

inside: ø ca. 1.7 mm outside: ø ca. 4.75 mm length: ca. 9.5 mm

#### System requirements

- Mac OS 12.0.1 or above
- Windows 8.1/8.1-64/10/10-64/11
- PC or laptop with a free USB Type-A port or
- PC or laptop with a free USB Type-C<sup>™</sup> or Thunderbolt<sup>™</sup> 3 port

#### Package content

- USB docking station
- Cable USB Type-A male to Type-B male, length ca. 1 m
- Cable USB-C<sup>™</sup> male to USB Type-B male, length ca. 1 m
- · Power supply
- User manual



# **Images**



















#### General

Function:	mirror and extend
Supported operating system:	Windows 10 32-Bit Windows 10 64-Bit Windows 8.1 32-Bit Windows 8.1 64-Bit Windows 11 Mac OS 12.0.1 or above

## **Technical characteristics**

Maximum screen resolution: 384	10 x 2160 @ 60 Hz
--------------------------------	-------------------

# **Physical characteristics**

Colour:
---------