Delock USB 2.0 Card Reader All in 1

Description

This card reader by Delock has six memory card slots and allows to read and write many different memory cards. The card reader can be connected to a PC or laptop via the USB Type-A interface.



Item no. 91471

EAN: 4043619914715

Country of origin: China

Package: Retail Box

Specification

- Connectors:
  1 x USB 2.0 Type-A male >
  1 x CF slot
  1 x SD / MMC slot
  1 x MS slot
  1 x xD slot
  1 x M2 slot
  1 x Micro SD slot
- Data transfer rate up to 480 Mbps
- Dimensions (LxWxH): ca. 56.6 x 43.5 x 13.2 mm
- Hot Swap, Plug & Play

- Supports following memory cards:
  Slot 1
  CF I, CF II, CF 4.0, CF Extreme, CF Extreme III, CF Extreme IV, CF Extreme IV UDMA, UDMA Extreme, UDMA 6 Extreme Pro, ULTIMA II, Micro Drive, Magicstor

  Slot 2
  SD, SD High Capacity (SDHC), SDXC, SD Ultra II, SD UDMA II, SD Extreme III, SDHC Turbo, SDHC Ultra, SDHC Extreme, SDHC Extreme III, Turbo-SD, Turbo Mini SD*, Mini

© 2024 by Delock. All names and symbols mentioned here are property of the respective producer.
Printing errors, changes and errors excepted.

SD*, Mini SDHC*, MMC-I, MMC-II, MMC plus, MMC plus Turbo, HS-MMC, HC-MMC, MMCmobile*, MMCmobile* Dual-Voltage, RS-MMC*, RS-MMC 4.0*

Slot 3
MS, High Speed MS (HS-MS), MS-ROM, MS Magic Gate, MS Pro, MS-Pro Magic Gate, MS-Duo, MS-Duo Magic Gate, MS-Pro Duo, MS-Pro HighSpeed, MS-Pro HG-Duo, MS-Pro Duo Magic Gate

Slot 4
xD, xD type M, xD type H

Slot 5
MS Micro (M2)

Slot 6
MicroSD, Micro SDHC, Micro SDHC Turbo, T-Flash, MMCmicro

*Adapter is required

System requirements

- Linux Kernel 2.4 or above
- Mac OS 8.6 or above
- Windows Server 2003
- Windows Vista/7/8.1/10
- PC or laptop with a free USB Type-A port

Package content

- USB 2.0 Card Reader All in 1
- USB 2.0 cable
- User manual

© 2024 by Delock. All names and symbols mentioned here are property of the respective producer.
Printing errors, changes and errors excepted.

Images







© 2024 by Delock. All names and symbols mentioned here are property of the respective producer.
Printing errors, changes and errors excepted.